



Updating D

- Unzip the archive with the new code.
- The folder containing the code, e.g. 'D-12-06' should be placed in the folder "...\dd\code".
- Open the file "dd_localsettings.sdv" that is found in the D root folder and update the version to the folder name of the code. The part to be edited is shown in blue in the example below.
- Note that it is not necessary to delete the folders with old code. Keeping these allow you to run previous versions if necessary.

An example of "dd_localsettings.sdv" is shown below. Parts to check or edit is shown in blue.

```
version;D-12-06b;Current version and name of subdirectory for
codes
defaultmethod;Default;Method to load on start
windowpos;[0.1 0.1 0.75 0.75];Position and size of main window
path_cdf;K:\CHROMBOX\DD\cdf
user;Anonymous; Specify user signature for info files
tracker;0; For development purposes
```

- Alternatively, you may select the new code by the following procedure:
- Open Chrombox D
- Press the [Settings] button down in the right corner
- Select [Load/Files]
- Select the code version and press [Save local settings]
- Restart Chrombox D.

